

UBI WORLD TV – UEC STB – OPTUS D2 SETTINGS

This guide will assist you to setup the UEC STB on Optus D2

UBI HOME TRANSPONDER

FREQUENCY	12644
SYMBOL RATE	22500
POLARISATION	HORIZONTAL
FEC	3/4

- STEP 1**
START ON ANY UBI CHANNEL
- STEP 2**
PRESS **MENU**
SCROLL DOWN TO **ADVANCED OPTIONS**
PRESS **OK**
- STEP 3**
PRESS **OK** ON **CHANGE DISH INSTALLATION**
- STEP 4**
TYPE IN PIN CODE **8 2 7 2**
IF YOU MAKE A MISTAKE PRESS THE LEFT ARROW TO DELETE THE WRONGLY ENTERED NUMBER
- STEP 5**
SCROLL DOWN TO **SIGNAL SETUP**
PRESS **OK**
- STEP 6**
PRESS **OK** ON **SIGNAL SETUP 1 (home)**
SIGNAL SETUP 1 (home) IS FOR UBI
- STEP 7**
ENTER THE NEW UBI SETTINGS
SIGNAL SOURCE **ENABLED**
FREQUENCY **12644**
SYMBOL RATE **22500**
POLARISATION **HORIZONTAL**
FEC **3/4**
PRESS **OK**
- STEP 8**
ONLY **SIGNAL SETUP 1 (home)** SHOULDVE HAVE AN ASTREIX * NEXT TO IT
THIS MEANS THAT ONLY UBI IS ENABLED
PRESS **EXIT**
- STEP 9**
SCROLL DOWN TO **TUNE & RESCAN**
PRESS **OK**
- STEP 10**
BE PATIENT WHILE THE **SCANNING** TAKES PLACE
- STEP 11**
IF ALL WENT OK THEN A UBI CHANNEL WILL APPEAR